



Lid open

Lid closed


### Mounting to desk




Ensure grips on both sides of the module are rotated flush against the sides first.



Lower the Horizon module into the cut-out hole in the desk. 1\*




Rotate the grips back out on either side of the module.




Tighten the bolts inside the module to clamp the grips to the desk.

### Lid operation




Lift up the lid from the front lip adjacent to the brush strip. Pivot back until vertical.




Gently slide the lid down into the module until it stops. Reverse steps to close.


### Contents



### Raising/lowering the module




Use both hands to lift up the module at both ends. Lift until a click is heard.




To lower, depress the side buttons as shown and gently lower the module to the bottom.

### Connecting to power

#### Connecting standard 3-pole connector




Plug the male 3-pole connector supplied as standard into a female powered connector.




Ensure the attached locking mechanism clicks into place on both connectors.

#### Disconnecting standard 3-pole connector




Use a suitable tool to release the locking mechanism.




Separate the connectors.

### Connecting data/AV (if applicable)




Offer up the data/AV cable connectors to the related ports on the module.




Connect cables from the module to the source. Use suitable cable management for safety.

### USB charging (if applicable)



Insert the USB connector from your device into the related port on the module.



Ensure the cable is securely connected.

### Additional information

#### Safety

- Installation is to be carried out in accordance with relevant Health & Safety regulations and only to be carried out by a skilled or competent person.
- The product should be installed to comply with the relevant national standards and be inspected and tested prior to being put into service (in the UK BS 7671 Wiring Regulations or BS 6396 Office and Educational Systems Best Practice).
- Isolate the supply before installation or repositioning. Any locking mechanisms must be used and fully engaged.
- Incorrect use could lead to risk of electrocution.
- Connectors must not be engaged or disengaged when under load or live.
- Product to be used only for the intended purpose of distributing power and data in office and commercial environments.
- Do not misuse, dismantle or re-configure the product because doing so will invalidate the warranty.

#### Standards

- Refer to the Declaration of Conformity.

#### Further guidance

- Fuse replacement only to be carried out by a skilled or competent person.
- Should the supply cable need replacing, contact CMD.

#### Product care

- Clean using a dry cloth. No abrasives or solvents to be used on the product.
- Do not drop or expose to moisture.