



Elite+ data module with 2x data sockets and 2x keystone blanks shown for illustration purposes.

Connecting to data


Installing pre-terminated data assemblies




At the back of the module, remove 4x screws and remove rear plate.



Feed the data cables of the pre-terminated data assemblies through front face of Elite+ module.




Feed data cables through side slots in Elite+ fascia.




Screw the rear plate back in place. Torque of 0.6Nm advised.


Contents



Mounting (under desk)




Place module in cable tray/basket and secure with suitable fixing devices if possible.




Mark hole positions and drill pilot holes. Fix with suitable screws. Do not over-tighten fixings.

Connecting to data (continued)


Installing data cables



Lift up the shutter on the front of the RJ45 sockets and insert the data connectors.




Push in gently until the connectors click into place. Use cable management for safety.




Connect to the data source. Use cable management for safety.

Keystone blanks



Fit keystone blanks into unused data apertures to prevent dust ingress (supplied separately).



The keystone blanks click into place if fitted correctly.

Additional Information

Safety

- Installation is to be carried out in accordance with relevant Health & Safety regulations and only to be carried out by a skilled or competent person.
- Product to be used only for the intended purpose of distributing data in office and commercial environments.
- Do not misuse, dismantle or re-configure the product because doing so will invalidate the warranty.

Standards

- Refer to the Declaration of Conformity.

Further Guidance

- Should the supply cable need replacing, contact CMD.
- Keystone blanks are supplied separately. For supply details contact CMD.

Product Care

- Clean using a dry cloth. No abrasives or solvents to be used on the product.
- Do not drop or expose to moisture.

